



85741183



IP20

**Blind time switch with display, Berker S.1/B.3/B.7, aluminium, matt, lacquered**

**Technical features**

**Functions**

Astronomic time shift	± 2 h
Running time	2 mn
Random number generator	± 15 mn
Power reserve	≈ 24 h

- reset function (to factory setting)
- with keylock
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)
- with switchover manual/automatic mode

**Controls and indicators**

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

**Main electrical features**

Nominal voltage	12 V
Frequency	- Hz

**Measurement**

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

**Detection**

- Not suitable for rain and wind sensors

**Materials**

Colour of design line	aluminium
Colour	aluminium
Material / workmanship	lacquered
Material	Plastic/metal

**Installation, mounting**

Installation mode	clamp fastening
-------------------	-----------------

**Settings**

Minimum slat adjustment time	≈ 250 ms
Lamella adjustment on button-press	< 0,5 s
Time	with automatic summer-/winter time switching (can be switched off)

- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- holiday programme for random variation of the operation times in automatic operation

### Equipment

Number of operation times for up/down	20
Self-retaining for 2 min on button-press	> 0,5 s
Change-over time for change of direction	< 0,6 s
- 2 independent preset programme memories, individually adaptable	

### Use

Differentiation characteristic 2 - Sales	with display
--	--------------

### Safety

- with dismantling protection

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	Blind control
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Electronics platform, Berker S.1, Berker B.3, Berker B.7

### Instructions

- Can be switched to orientation led by extension unit.