




85745289



## KNX radio timer quicklink with display, Berker S.1/B.3/B.7, polar white glossy

### Technical features

#### Functions

Astronomic time shift	± 2 h
Random number generator	± 15 mn
Power reserve	≈ 24 h
<ul style="list-style-type: none"> <li>- ETS additional functions: +6 scenes, operating mode on/off, scene loading, time dimming value, push-button, status display</li> <li>- reset function (to factory setting)</li> <li>- Configurable transmission and/or reception behaviour</li> <li>- Party function, no execution of automatic, radio and extension unit commands (switch protection)</li> <li>- with keylock</li> <li>- easy additional functions: +6 scenes, dimming, 1 up/down button control, priority</li> <li>- quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control</li> <li>- with switchover manual/automatic mode</li> </ul>	

#### Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

#### Connectivity

Radio protocol	KNX Radio
----------------	-----------

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

#### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
Running accuracy	± 3 min/year

#### Materials

Colour of design line	polar white
Surface appearance	glossy

#### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

#### Settings

Time	with automatic summer-/winter time switching (can be switched off)
<ul style="list-style-type: none"> <li>- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable</li> <li>- standalone programme, radio and extension unit commands are not executed</li> <li>- holiday programme for random variation of the switching times in automatic operation</li> </ul>	

#### Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Number of switching times for on/off	20
<ul style="list-style-type: none"> <li>- 2 independent preset programme memories, individually adaptable</li> </ul>	

**Use**

---

Differentiation characteristic 2 - Sales	with display
--	--------------

---

**Safety**

---

Protection index IP	IP20
---------------------	------

---

- with dismantling protection

---

**Use conditions**

---

Operating temperature	-5...45 °C
-----------------------	------------

---

- low intrinsic energy requirement

---

**Identification**

---

Application, usage	Light control, KNX radio- operating systems
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Electronics platform, Berker S.1, Berker B.3, Berker B.7

---