


281901



Rotary dimmer 400 W with soft-lock, Light control, others

Technical features

Functions

- bulb-preserving soft startup

Main electrical features

| | |
|-----------------|-------|
| Nominal voltage | 230 V |
| Frequency | 50 Hz |

Voltage

| | |
|-------------------|----------|
| Operating voltage | 230 V AC |
|-------------------|----------|

Fuse

| | |
|----------------|---|
| Fine-wire fuse | T 1.6 H 250 |
| Fuse | short-circuit and overload proof (fine-wire fuse) |

Power

| | |
|-------------------------|-------|
| Loss power at full load | ≈ 4 W |
|-------------------------|-------|

Materials

| | |
|----------|----------------|
| Colour | not applicable |
| Material | Plastic/metal |

Dimensions

| | |
|------------------|------|
| Axis dimension Ø | 4 mm |
|------------------|------|

Incandescent bulbs control

| | |
|--|------------|
| 230 V incandescent lamps and halogen lamps | 60...400 W |
|--|------------|

Installation, mounting

| | |
|-------------------|---------------------|
| Installation mode | with spreader claws |
|-------------------|---------------------|

Connection

| | |
|------------------------|----------------|
| Type of load | Resistive load |
| - with screw terminals | |

Equipment

- phase cut-on
- with rotary on/off switch

Use

| | |
|--|----------------|
| Differentiation characteristic 3 - Sales | with soft-lock |
|--|----------------|

Use conditions

| | |
|-----------------------|-----------|
| Operating temperature | 5...25 °C |
|-----------------------|-----------|

Identification

| | |
|--------------------------|-------------------|
| Application, usage | Light control |
| Main design line | Light control |
| Secondary design line(s) | House electronics |

Instructions

| | |
|------------------|---|
| Information text | Possible to change fuse without removing cover. |
|------------------|---|
