




85745126



**KNX radio blind time switch quicklink with display, Berker Q.1/Q.3/Q.7/Q.9, anthracite velvety, lacquered**

**Technical features**

**Functions**

Astronomic time shift	± 2 h
Running time	2 mn
Random number generator for holiday program	± 15 mn
Power reserve	≈ 24 h

- ETS additional functions: +6 scenes, operating mode, status display, 2 x alarm
- reset function (to factory setting)
- with keylock
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)
- Configurable transmission and/or reception behaviour
- easy additional functions: +6 scenes, 1 up/down operating mode
- slat position storable for scene
- scene opening via KNX radio appliances
- quicklink functions for integration into the individual, group and master control of blinds/shutters
- quicklink functions: blind, 2 scenes, forced control, up/down push-button
- with switchover manual/automatic mode

**Controls and indicators**

- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable
- LC display illuminated during operation

**Connectivity**

Radio protocol	KNX Radio
----------------	-----------

**Power**

Radio transmission power	< 10 mW
--------------------------	---------

**Measurement**

Relative humidity (without condensation)	0...65 % (without condensation)
Running accuracy	± 3 min/year

**Detection**

- sun protection and twilight-controlled lowering with radio brightness sensor

**Materials**

Colour of design line	anthracite
RAL colour	RAL 7021 - Black grey
Material / workmanship	lacquered
Surface appearance	velvety

**Connection**

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Settings

Minimum slat adjustment time	≈ 150 ms
Lamella adjustment on signal duration	< 1 s
Lamella adjustment on button-press	< 0,5 s
Time	with automatic summer-/winter time switching (can be switched off)
<ul style="list-style-type: none"><li>- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable</li><li>- standalone programme, radio and extension unit commands are not executed</li><li>- holiday programme for random variation of the operation times in automatic operation</li></ul>	

### Equipment

Number of operation times for up/down	20/day
Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Self-retaining for 2 min on signal length	> 1 s
Self-retaining for 2 min on button-press	> 0,5 s
Change-over time for change of direction	< 0,6 s
<ul style="list-style-type: none"><li>- 2 independent preset programme memories, individually adaptable</li></ul>	

### Use

Differentiation characteristic 2 - Sales	with display
------------------------------------------	--------------

### Safety

Protection index IP	IP20
<ul style="list-style-type: none"><li>- with dismantling protection</li></ul>	

### Use conditions

Operating temperature	-5...45 °C
<ul style="list-style-type: none"><li>- low intrinsic energy requirement</li></ul>	

### Identification

Application, usage	Blind control, KNX radio- operating systems
Main design line	Berker Q.1/Q.3/Q.7/Q.9
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

### Instructions

- Can be switched to orientation led by extension unit.