



85346124



2.2 m

IP20

**KNX radio motion detector comfort 2.2 m quicklink Berker Q.1/Q.3/Q.7/Q.9**

Technical features

**Functions**

- µ-processor controlled mode of operation
- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value, brightness display, movement scene loading, no movement scene loading
- reset function (to factory setting)
- Party function for switching on for 2 hours
- with memory function for presence simulation
- with keylock
- Switch-off pre-warning on dimmer inserts
- Teach function for response brightness via button
- scene opening via KNX radio appliances
- scene saving lockable
- quicklink functions: switching, dimming, 2 scenes, time switching, NO contact push-button, Memory, forced control, Master-Slave

**Compatibility**

- optional operation of extension units using installation push-button

**Controls and indicators**

- remote control via quicklink transmitter
- with configuration and function button
- with button for on/off/automatic/memory/party function

**Connectivity**

Radio protocol	KNX Radio
Receiver category	2

**Frequency**

Radio transmission frequency	868,3 MHz
------------------------------	-----------

**Power**

Radio transmission power	< 10 mW
--------------------------	---------

**Measurement**

Relative humidity (without condensation)	0...65 % (without condensation)
Detection field, rectangular shaped	≈ 8 x 12 m

**Reach distance**

Range, frontal	≈ 8 m
Range, frontal (at 1.1 m installation height)	≈ 4 m
Range, side	each ≈ 6 m
Range, side (at 1.1 m installation height)	each ≈ 3 m

**Detection**

Number of detection levels	2
Detection angle, settable	each side ≈ 45...90 °

### Materials

Colour of design line	aluminium
RAL colour	RAL 9006 - White aluminium
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	velvety

### Dimensions

Assembling height	34 mm
Nominal mounting height	2,2 m

### Lighting control

Response brightness, adjustable	≈ 5...1 000 lx, daytime operation
---------------------------------	-----------------------------------

### LED control

LED	LED application module/insert compatibility display, with configuration and function LEDs, with operation and status LED, red/green/orange
-----	--

### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Settings

Response sensitivity, settable	10...100 %
Delay time, adjustable	≈ 1 s...3 h
Switch-off pre-warning to dimming value 50% for	30 s

### Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

### Safety

- with dismantling protection

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	Motion detector, KNX radio- sensors
Main design line	Berker Q.1/Q.3/Q.7/Q.9
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9