



85342229





### IR motion detector comfort 2.2 m Berker Q.1/Q.3/Q.7/Q.9, polar white velvety

Technical features

### **Architecture**

Fixing mode flush-mounting

#### **Functions**

# Operating mode

step operation with immunity time (e.g. for stair light/impact current circuits)

- $\mu$ -processor controlled mode of operation
- Teach function for response brightness via button
- with keylock
- Party function for switching on for 2 hours
- with memory function for presence simulation

#### **Controls and indicators**

- with button for on/off/automatic

## **Tripping**

immunity time ≈ 10 s

#### Measurement

Relative humidity (without condensation) 0...65% (without condensation)

Detection field, rectangular shaped  $\approx 8 \times 12 \text{ m}$ 

#### Reach distance

Range, frontal  $\approx 8 \text{ m}$  Range, side each  $\approx 6 \text{ m}$ 

# Detection

Number of detection levels 3

Detection angle, settable each side  $\approx 45...90^{\circ}$ 

### Materials

Colour of design linepolar whiteColourpolarwhiteMaterialthermoplastic

## **Dimensions**

Assembling height 34 mm

Nominal mounting height 2,2 m

# **Lighting control**

Response brightness, adjustable  $\approx 5...1000 \text{ lx}$ , daytime operation

# **LED** control

LED with operation and status LED, red/green/orange,
LED application module/insert compatibility display



# Settings

Response value luminosity adjustable	yes
Response value sensitivity adjustable	yes
Response sensitivity, settable	10100 %
Short time mode	200 ms
Delay time	≈ 180 s
Delay time, adjustable	≈ 10 s30 mn
Switch-off pre-warning to dimming value 50% for	30 s
Safety	
Protection index IP	IP20
- with dismantling protection	
Use conditions	
Operating temperature	-545 °C
- low intrinsic energy requirement	
Identification	
Application, usage	Light control, Motion detector
Main design line	Berker Q.1/Q.3/Q.7/Q.9
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9
Instructions	
Information text	Continuous direct sunlight penetrating the upward- pointing detection plane can result in failure of the motion detector.
	Only suitable for indoor areas!