

Touch dimmer (R, L) Electronics platform

Technical features

 when cover is detached, the switch status is retained (wallpaper function) bulb-preserving soft startup 	
Main electrical features	
Frequency	50/60 H
Voltage	
Operating voltage	230 V A
Fuse	
Fuse	short-circuit and overload proof (electronic fuse
Power	
Dimmable conventional transformers	25400 V
Power consumption (standby)	< 0,3 \
Measurement	
Relative humidity (without condensation)	065 % (without condensation
Extension unit input	with extension unit input for push-button (N contact), single-surface operation and motio detector extension un
Materials Colour	not applicabl
Material	Plastic/met
 no conductive connection between supporting ring 	g and spreading claws
Dimensions	
Insertion depth	32 mi
Incandescent bulbs control	
Incandescent bulbs control 230 V incandescent lamps and halogen lamps	25400
230 V incandescent lamps and halogen lamps	25400
230 V incandescent lamps and halogen lamps	
230 V incandescent lamps and halogen lamps Installation, mounting Installation mode	
230 V incandescent lamps and halogen lamps Installation, mounting Installation mode Connection	with spreader claw
	with spreader clav 2 x 1,5/1 x 2,5 mn
230 V incandescent lamps and halogen lamps Installation, mounting Installation mode Connection Screw terminals (max.)	with spreader clav 2 x 1,5/1 x 2,5 mn
230 V incandescent lamps and halogen lamps Installation, mounting Installation mode Connection Screw terminals (max.) Number of substations	25400 with spreader claw 2 x 1,5/1 x 2,5 mm unlimite
230 V incandescent lamps and halogen lamps Installation, mounting Installation mode Connection Screw terminals (max.) Number of substations - with screw terminals	with spreader clav 2 x 1,5/1 x 2,5 mn

Equipment

Main design line	Electronics platform
Application, usage	Motion detector, Light control, KNX radio- operating systems
Identification	
- low intrinsic energy requirement	
Operating temperature	-545 °C
Use conditions	
 phase cut-on switch-on brightness level can be stored safe after power failure 	