



85655229



IP20

KNX radio wall-transmitter 1gang flat quicklink Berker Q.1/Q.3/Q.7/Q.9, polar white velvety

Technical features

Functions

- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration button

Connectivity

| | |
|-------------------|-----------|
| Radio protocol | KNX Radio |
| Receiver category | 2 |

Frequency

| | |
|------------------------------|-----------|
| Radio transmission frequency | 868,3 MHz |
|------------------------------|-----------|

Power

| | |
|--------------------------|---------|
| Radio transmission power | < 10 mW |
|--------------------------|---------|

Measurement

| | |
|--|---------------------------------|
| Relative humidity (without condensation) | 0...65 % (without condensation) |
|--|---------------------------------|

Battery

| | |
|--|-----|
| Battery service life [years] | ≈ 5 |
| - with lithium coin cell battery 3 V type: CR 2430 | |

Materials

| | |
|-----------------------|-----------------------|
| Colour of design line | polar white |
| RAL colour | RAL 9010 - Pure white |
| Material | thermoplastic |
| Surface appearance | velvety |

Dimensions

| | |
|-------------------|-------|
| Assembling height | 14 mm |
|-------------------|-------|

LED control

| | |
|-----|---|
| LED | with transmission status and battery status LED, red/green/orange, with configuration LED |
|-----|---|

Installation, mounting

| | |
|-------------------|---|
| Installation mode | for flat surface mounting and extension of combinations |
|-------------------|---|

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

- toolless quicklink configuration using buttons and LED display
- top and bottom operating area are freely configurable

Equipment

| | |
|---------------------------|------------------------------|
| Number of radio channels | 2 |
| Number of quicklink links | max. 20 transmitter/receiver |
| Transmitter duty cycle | 1 % |

Safety

- with dismantling protection

Use conditions

| | |
|------------------------------------|------------|
| Operating temperature | -5...45 °C |
| - low intrinsic energy requirement | |

Identification

| | |
|--------------------------|--|
| Application, usage | KNX radio- operating systems |
| Main design line | Berker Q.1/Q.3/Q.7/Q.9 |
| Secondary design line(s) | Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9 |