




85745279



KNX radio timer quicklink with display, Berker K.1, polar white glossy

Technical features

Functions

Astronomic time shift	± 2 h
Random number generator	± 15 mn
Power reserve	≈ 24 h

- ETS additional functions: +6 scenes, operating mode on/off, scene loading, time dimming value, push-button, status display
- reset function (to factory setting)
- Configurable transmission and/or reception behaviour
- Party function, no execution of automatic, radio and extension unit commands (switch protection)
 - with keylock
- easy additional functions: +6 scenes, dimming, 1 up/down button control, priority
- quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control
 - with switchover manual/automatic mode

Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

Connectivity

Radio protocol	KNX Radio
----------------	-----------

Power

Radio transmission power	< 10 mW
--------------------------	---------

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
Running accuracy	± 3 min/year

Materials

Colour of design line	polar white
Surface appearance	glossy

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

Time	with automatic summer-/winter time switching (can be switched off)
------	--

- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- standalone programme, radio and extension unit commands are not executed
- holiday programme for random variation of the switching times in automatic operation

Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Number of switching times for on/off	20

- 2 independent preset programme memories, individually adaptable

Use

Differentiation characteristic 2 - Sales with display

Safety

Protection index IP IP20
- with dismantling protection

Use conditions

Operating temperature -5...45 °C
- low intrinsic energy requirement

Identification

Application, usage Light control, KNX radio- operating systems
Main design line Berker K.1
Secondary design line(s) Berker.Net, Berker K.1
