



85741188



IP20

## Blind time switch with display, Berker S.1/B.3/B.7, polar white matt

### Technical features

### Functions

Astronomic time shift	± 2 h
Running time	2 mn
Random number generator	± 15 mn
Power reserve	≈ 24 h
<ul style="list-style-type: none"> <li>- reset function (to factory setting)</li> <li>- with keylock</li> <li>- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)</li> <li>- with switchover manual/automatic mode</li> </ul>	

### Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

### Main electrical features

Nominal voltage	12 V
Frequency	- Hz

### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

### Detection

- Not suitable for rain and wind sensors

### Materials

Colour of design line	polar white
Colour	polarwhite
Material	Plastic/metal

### Installation, mounting

Installation mode	clamp fastening
-------------------	-----------------

### Settings

Minimum slat adjustment time	≈ 250 ms
Lamella adjustment on button-press	< 0,5 s
Time	with automatic summer-/winter time switching (can be switched off)
<ul style="list-style-type: none"> <li>- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable</li> <li>- holiday programme for random variation of the operation times in automatic operation</li> </ul>	

### Equipment

Number of operation times for up/down	20
Self-retaining for 2 min on button-press	> 0,5 s
Change-over time for change of direction	< 0,6 s
<ul style="list-style-type: none"> <li>- 2 independent preset programme memories, individually adaptable</li> </ul>	

---

**Use**

---

Differentiation characteristic 2 - Sales with display

---

**Safety**

---

- with dismantling protection

---

**Use conditions**

---

Operating temperature -5...45 °C

---

- low intrinsic energy requirement

---

**Identification**

---

Application, usage Blind control

---

Main design line Berker S.1/B.3/B.7

---

Secondary design line(s) Electronics platform, Berker S.1, Berker B.3, Berker  
B.7

---

**Instructions**

---

- Can be switched to orientation led by extension unit.

---