



85741126



IP20

Blind time switch with display, Berker Q.1/Q.3/Q.7/Q.9, anthracite velvety, lacquered

Technical features

Functions

Astronomic time shift	± 2 h
Running time	2 mn
Random number generator	± 15 mn
Power reserve	≈ 24 h

- reset function (to factory setting)
- with keylock
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)
- with switchover manual/automatic mode

Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

Main electrical features

Nominal voltage	12 V
Frequency	- Hz

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

Detection

- Not suitable for rain and wind sensors

Materials

Colour of design line	anthracite
Colour	anthracite
Material / workmanship	lacquered
Material	Plastic/metal

Installation, mounting

Installation mode	clamp fastening
-------------------	-----------------

Settings

Minimum slat adjustment time	≈ 250 ms
Lamella adjustment on button-press	< 0,5 s
Time	with automatic summer-/winter time switching (can be switched off)

- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- holiday programme for random variation of the operation times in automatic operation

Equipment

Number of operation times for up/down	20
Self-retaining for 2 min on button-press	> 0,5 s
Change-over time for change of direction	< 0,6 s
- 2 independent preset programme memories, individually adaptable	

Use

Differentiation characteristic 2 - Sales	with display
--	--------------

Safety

- with dismantling protection

Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

Identification

Application, usage	Blind control
Main design line	Berker Q.1/Q.3/Q.7/Q.9
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

Instructions

- Can be switched to orientation led by extension unit.