


2898



**DALI rotary potentiometer with power supply Soft-lock, Light control**

**Technical features**

**Functions**

- for switching and controlling electr. ballasts and Tronic transformer with DALI/DSI interface

**Controls and indicators**

- with soft-lock

**Main electrical features**

Nominal voltage	230 V
Rated voltage	230 V AC
Frequency	50/60 Hz

**Voltage**

DALI voltage	16 V DC
--------------	---------

**Electric current**

Output current	max. 52 mA
----------------	------------

**Fuse**

Fuse	short-circuit and overload proof (electronic fuse)
------	--

**Power**

Power consumption	≤ 2 W
-------------------	-------

**Dimensions**

Axis dimension Ø	4 mm
------------------	------

**Connection**

Quantity of DALI devices with 4 active DALI potentiometers in parallel	104
Quantity of DALI devices with an active DALI potentiometer	26
- with screw terminals	

**Cable**

DALI cable length at 1.5 mm <sup>2</sup>	max. 200 m
--	------------

**Settings**

- basic brightness programmable

**Scope of delivery**

- with incremental encoder

### Equipment

- switch-on brightness level can be stored safe after power failure
- supplies the necessary control current for additional DALI users in the active operation to mains voltage
- parallel connection of max. 4 active DALI potentiometers possible
- without mains voltage in passive operation on DALI voltage the unit serves as an additional control
- with on/off pressure switch

### Use

Differentiation characteristic 3 - Sales	Soft-lock
--	-----------

### Identification

Application, usage	Light control
Main design line	Light control

### Instructions

Information text	Not suitable for combining with other DALI sensors or central units.
------------------	--