



85241122



IP20

Blind time switch Berker Q.1/Q.3/Q.7/Q.9

Technical features

Functions

| | |
|--|------|
| Venetian blind movement time | 2 mn |
| - Memory function for automatic execution of learned up and down times with position | |
| - Party function, no execution of automatic, radio and extension unit commands (lock-out protection) | |

Controls and indicators

- activation of the party function using buttons in up and down direction > 20 sec.

Main electrical features

| | |
|-----------------|------|
| Nominal voltage | 12 V |
| Frequency | - Hz |

Measurement

| | |
|--|---------------------------------|
| Relative humidity (without condensation) | 0...65 % (without condensation) |
|--|---------------------------------|

Detection

- Not suitable for rain and wind sensors

Materials

| | |
|-----------------------|---------------|
| Colour of design line | white |
| Colour | white |
| Material | thermoplastic |

LED control

| | |
|-----|--|
| LED | LED application module/insert compatibility display, with status LED for memory and party function, red/orange, with indicator LED for lock-out protection |
|-----|--|

Installation, mounting

| | |
|-------------------|-----------------|
| Installation mode | clamp fastening |
|-------------------|-----------------|

Settings

| | |
|------------------------------------|----------------------------|
| Lamella adjusting time | (adjustable) 50 ms...2,5 s |
| Minimum slat adjustment time | ≈ 250 ms |
| Delay time, adjustable | 0...500 s |
| Lamella adjustment on button-press | < 0,4 s |

Equipment

| | |
|--|---------|
| Self-retaining for 2 min on button-press | > 0,4 s |
| Change-over time for change of direction | < 0,6 s |

Safety

- with dismantling protection

Use conditions

Operating temperature -5...45 °C

- low intrinsic energy requirement

Identification

Application, usage Blind control

Main design line Berker Q.1/Q.3/Q.7/Q.9

Secondary design line(s) Electronics platform, Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

Instructions

- Can be switched to orientation led by extension unit.
