



85245122



IP20

quicklink

## KNX radio blind button quicklink

### Technical features

### Functions

Venetian blind movement time	2 mn
------------------------------	------

- ETS additional functions: +6 scenes, operating mode, status display, 2 x alarm
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)
- Configurable transmission and/or reception behaviour
- Memory function for automatic execution of learned up and down times with position
- reset function (to factory setting)
- easy additional functions: +6 scenes, 1 up/down operating mode
- slat position storable for scene
- scene opening via KNX radio appliances
- quicklink functions: blind, 2 scenes, memory, forced control, up/down push-button

### Controls and indicators

- activation of the party function using buttons in up and down direction > 20 sec.
- with configuration and function button

### Connectivity

Radio protocol	KNX Radio
----------------	-----------

### Power

Radio transmission power	< 10 mW
--------------------------	---------

### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

### Detection

- sun protection and twilight-controlled lowering with radio brightness sensor

### Materials

Colour of design line	white
RAL colour	RAL 1013 - Oyster white
Material	thermoplastic
Surface appearance	velvety

### LED control

LED	with status LED for memory and party function, red/orange, with configuration and function LEDs, with indicator LED for lock-out protection, LED application module/insert compatibility display
-----	--

### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Settings

---

Lamella adjusting time	(adjustable) 50 ms...2,5 s
Minimum slat adjustment time	≈ 150 ms
Lamella adjustment on signal duration	< 1 s
Lamella adjustment on button-press	< 0,4 s

---

- toolless quicklink configuration using buttons and LED display

---

### Equipment

---

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Self-retaining for 2 min on signal length	> 1 s
Self-retaining for 2 min on button-press	> 0,4 s
Change-over time for change of direction	< 0,6 s

---

### Safety

- 
- with dismantling protection
- 

### Use conditions

---

Operating temperature	-5...45 °C
-----------------------	------------

---

- low intrinsic energy requirement

---

### Identification

---

Application, usage	Blind control, KNX radio- operating systems
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

---