



85166100



IP55

quicklink

## KNX radio switch actuator 2gang surface-mounted Electronics platform, white

### Technical features

#### Architecture

Fixing mode surface-mounting

#### Functions

- ETS additional functions: +6 scenes, operating mode on/off, status display
- reset function (to factory setting)
- Repeat function can be activated to increase the radio range
- easy additional functions: +6 scenes
- scene saving lockable
- scene opening via KNX radio appliances
- quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control

#### Controls and indicators

- with manual operation on/off per channel
- with configuration and function button

#### Connectivity

Bus system radio frequent	no
Bus system LON	no
Bus system Powernet	no
Radio protocol	KNX Radio
Receiver category	2

#### Electric current

Switching current 10 A/230 V AC1 A /230 V AC1

#### Frequency

Radio reception frequency 868,3 MHz

#### Power

Output power	2300 W
Conventional transformers	600 VA
Electronic transformers	per channel 600 W
Radio transmission power	< 10 mW
C-load	no

#### Measurement

Relative humidity (without condensation) 0...65 % (without condensation)

#### Materials

Colour of design line	white
Colour independent of design lines	white

#### Dimensions

Length	150 mm
Height	150 mm
Width	85 mm

### Lighting control

Fluorescent lamps with electronical ballast (EB)	per channel 6 x 58 W
- uncompensated	per channel 600 VA

### Fluorescent bulbs control

Energy-saving lamps	per channel 100 W
Compact fluorescent lamps	18 W

### LED control

230V LED lamps	je Kanal 100 W
LED	with control LED for On/Off, with configuration and function LEDs

### Incandescent bulbs control

230 V incandescent lamps and halogen lamps	per channel 1500 W
--	--------------------

### Connection

- with screw-in lift terminals
- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Cable

- with mounting plates and strain reliefs

### Settings

- toolless quicklink configuration using buttons and LED display

### Scope of delivery

Bus connection included	no
-------------------------	----

### Equipment

Number of outputs	2
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %
Different phases connectable	no

### Use conditions

Operating temperature	-10...55 °C
- low intrinsic energy requirement	

### Identification

Application, usage	KNX radio - actuators
Product family	product family: output
Main design line	Electronics platform