




2898



## DALI rotary potentiometer with power supply Soft-lock, Light control

### Technical features

### Functions

- for switching and controlling electr. ballasts and Tronic transformer with DALI/DSI interface

### Controls and indicators

- with soft-lock

### Main electrical features

Nominal voltage	230 V
Rated voltage	230 V AC
Frequency	50/60 Hz

### Voltage

DALI voltage	16 V DC
--------------	---------

### Electric current

Output current	max. 52 mA
----------------	------------

### Fuse

Fuse	short-circuit and overload proof (electronic fuse)
------	--

### Power

Power consumption	≤ 2 W
-------------------	-------

### Dimensions

Axis dimension Ø	4 mm
------------------	------

### Connection

Quantity of DALI devices with 4 active DALI potentiometers in parallel	104
Quantity of DALI devices with an active DALI potentiometer	26
- with screw terminals	

### Cable

DALI cable length at 1.5 mm <sup>2</sup>	max. 200 m
--	------------

### Settings

- basic brightness programmable

### Scope of delivery

- with incremental encoder

### Equipment

---

- switch-on brightness level can be stored safe after power failure
  - supplies the necessary control current for additional DALI users in the active operation to mains vo
  - parallel connection of max. 4 active DALI potentiometers possible
  - without mains voltage in passive operation on DALI voltage the unit serves as an additional control
  - with on/off pressure switch
- 

### Use

---

Differentiation characteristic 3 - Sales Soft-lock

---

### Identification

---

Application, usage Light control

Main design line Light control

---

### Instructions

---

Information text Not suitable for combining with other DALI sensors  
or central units.

---