



6768766014



Socket outlet with earthing pin with enhanced touch protection, Berker Q.1/Q.3/Q.7/Q.9, orange velvety

Technical features

Architecture

| | |
|-----------------|----------------|
| Fixing mode | flush-mounting |
| - 2pole + earth | |

Connectivity

| | |
|------------------|-------|
| Type of USB port | other |
|------------------|-------|

Main electrical features

| | |
|-----------------|----------|
| Nominal voltage | 250 V |
| Rated voltage | 250 V AC |
| Frequency | 50/60 Hz |
| Rated current | 16 A |

Cover, door

| | |
|-------|---------------------|
| Cover | Central cover plate |
|-------|---------------------|

Materials

| | |
|------------------------------|--------------------------|
| Design lines special colours | orange |
| Colour | orange |
| Colour | orange |
| RAL colour | RAL 2003 - Pastel orange |
| Material | duroplastic |
| Surface appearance | velvety |

Dimensions

| | |
|-----------------------------------------|---------|
| Insertion depth | 32 mm |
| Installation depth, flush-mounted boxes | 31 mm |
| Mirror depth | 14,5 mm |

Installation, mounting

| | |
|-------------------|---------------------|
| Installation mode | with spreader claws |
|-------------------|---------------------|

Connection

| | |
|--------------------------|--------------------------|
| Connection terminals | according to IEC 60884-1 |
| - with plug-in terminals | |

Use

| | |
|------------------------------------------|--------------------------------|
| Differentiation characteristic 2 - Sales | with enhanced touch protection |
|------------------------------------------|--------------------------------|

Safety

| | |
|-----------------------------------------------|--------------------------|
| IK protection code against mechanical impacts | 02 |
| Enhanced contact protection | according to IEC 60884-1 |
| - Enhanced contact protection | |

Identification

| | |
|--------------------------|------------------------------------------------|
| Main design line | Berker Q.1/Q.3/Q.7/Q.9 |
| Secondary design line(s) | Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9 |
