



85275120



KNX radio blind actuator 1gang/binary input 2gang flush-mounted Electronics platform, lighth grey

Technical features

Architecture

Bus system	yes
Number of blinds/shutters outputs	1

Functions

Bus module detachable	no
<ul style="list-style-type: none"> - ETS additional functions: +6 scenes, operating mode, 1 up/down button control, 2 x alarm, status display - ETS additional function: repeater function - reset function (to factory setting) - scene saving lockable - scene opening via KNX radio appliances - quicklink functions: blind, 2 scenes, forced control, up/down push-button 	

Configuration

- with 2 mechanically and electrically mutually-locked relay contacts

Controls and indicators

Indicator lamp	yes
<ul style="list-style-type: none"> - with manual operation up/down - Activation, for example through switch, push-button, timer, blind timer switch - with configuration and function button 	

Connectivity

Bus system radio frequent	yes
Bus system LON	no
Bus system Powernet	no
Radio protocol	KNX Radio
Receiver category	2
<ul style="list-style-type: none"> - with 2 independent, mains supplied, binary inputs for potential-free contacts 	

Main electrical features

Type of supply voltage	AC
Frequency	50 Hz

Voltage

System supply voltage	230V AC
-----------------------	---------

Electric current

Number of entry circuits	2
Maximum switching current	3 A

Frequency

Radio reception frequency	868,3 MHz
---------------------------	-----------

Power

Contact rating with 230 V in AC1	690 W
Total power loss under IN	450 mW
Power dissipation per coil	150 mW
Radio transmission power	< 10 mW

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

Dimensions

Dimensions (Ø x H)	53 x 27 mm
Diameter	53 mm
Height	27 mm

LED control

LED	with configuration and function LEDs, with control LED (relay closed)
-----	---

Installation, mounting

Installation mode	for installation behind flush-mounted inserts
-------------------	---

Connection

Connection cross-sect. flexible conductor	0,5 / 1,5mm ²
Connection cross-sect. rigid cable	0,5 / 1,5mm ²
Conductor cross-section	0,75...2,5 mm ²
Number of contacts	1
Connection	with 2 independent battery-supplied binary inputs for potential-free contacts
Type of connection	with screw
<ul style="list-style-type: none"> - with screw-in lift terminals - integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system 	

Cable

Binary cable length, extendable to	max. 5 m
------------------------------------	----------

Settings

Supported configuration modes	system, easy, PB
Lamella adjustment on signal duration	< 1 s
- toolless quicklink configuration using buttons and LED display	

Equipment

Number of radio channels	2
Number of quicklink links	max. 20 transmitter/receiver
Self-retaining for 2 min on signal length	> 1 s
Transmitter duty cycle	1 %
Change-over time for change of direction	< 0,6 s
With slide for manual switch	yes

Use conditions

Operating temperature	-10...50 °C
Storage/transport temperature	-20...70 °C
- low intrinsic energy requirement	

Identification

Application, usage	KNX radio - actuators
Product family	product family: output
Device family	TRM
Main design line	Electronics platform
Secondary design line(s)	Berker.Net
