



80161869



**Push-button 1gang and RGB LED, with integrated temperature sensor, KNX - Berker R.1/R.3/Serie 1930/R.classic, polar white glossy**

**Technical features**

**Architecture**

Fixing mode	flush-mounting
Technical version	1gang

**Functions**

With room temperature controller	no
<ul style="list-style-type: none"> <li>- operating concept "independent push-button" function predefined</li> <li>- operating concept for "roller shutter/blind" function predefined</li> <li>- switching of scenes (1..8) possible</li> <li>- Orientation LED can be controlled via object</li> <li>- brightness value of the status LED for day/nighttime operation preset, status LED for day/nighttime operation can be controlled via object</li> <li>- integrated temperature sensor with output of the measured values</li> <li>- Colour of status LED uniformly adjustable for complete device</li> <li>- push-button functions: including switching, dimming, roller shutter/blind, timer, priority, temperature setpoint adjustment, operating mode changeover</li> <li>- Function for manual interruption of automatic functions already triggered</li> <li>- operating surfaces as buttons (single-surface operation) and rockers (two-surface operation)</li> <li>- the brightness of status LEDs are individually adjustable for button/ rocker function</li> <li>- brightness value of the status LEDs for day/nighttime operation adjustable via object or manually</li> <li>- value transmitter for dimming, position, brightness temperature values 1 and 2 byte</li> <li>- button/rocker functions for switching, dimming, roller shutter/blind, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, automatic control deactivation</li> <li>- integrated temperature sensor with output of the measured values via object</li> <li>- button functions for switching, dimming, roller shutter/blind, timer, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, 2-channel mode, step switch, automatic control deactivation</li> <li>- rocker functions for switching, dimming, roller shutter/blind, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, 2-channel mode, automatic control deactivation</li> <li>- parameter defineable lock function</li> <li>- 3-step switch, function for incremental selection of up to 7 stored values</li> <li>- Status LED configurable in its colour per button</li> </ul>	

**Compatibility**

- extension unit for light scene push-button

**Controls and indicators**

With LED indication	yes
Number of buttons	1
<ul style="list-style-type: none"> <li>- operating areas configurable as one or two-area operation</li> </ul>	

**Electric current**

Bus current consumption (data transfer)	max. 20 mA
---	------------

**Power**

Power consumption, KNX	≈ 150 mW
------------------------	----------

**Measurement**

- value transmitter for dimming, position, brightness and temperature values 1 and 2 byte

**Screen**

With display	no
--------------	----

### Materials

Colour of design line	polar white
Colour independent of design lines	polar white
Colour	polarwhite
RAL colour	RAL 9010 - Pure white
Material	thermoplastic
Surface appearance	glossy
Surface protection	Brilliant
Type of surface treatment	untreated
Material family	Plastic

### LED control

LED	with white operating LED, with 2 RGB status LEDs per rocker
-----	---

### Connection

- for bus coupling unit flush-mounted

### Settings

Supported configuration modes	system, easy
- single and two push-button operation parameterisable	

### Scope of delivery

Bus connection included	no
-------------------------	----

### Accessories included

Inscribable, with labelling field	no
-----------------------------------	----

### Equipment

Number of actuation points	2
With anti-theft/dismantling protection	no
Product type:	product type: push-button 1 gang

### Use

Differentiation characteristic 2 - Sales	and RGB LED
Differentiation characteristic 3 - Sales	with integrated temperature sensor

### Safety

Protection index IP	IP20
Halogen free	no
- with dismantling protection	
- alarm telegram after disconnection from bus coupling unit 1 bit or 1 byte	

### Use conditions

Operating temperature	-5...45 °C
Storage/transport temperature	-20...70 °C (storage at > 45°C reduces the service life)
- integrated temperature sensor with output of the measured values via object	

#### Identification

Application, usage	KNX - operating systems
Product family	product family: push-button
Main design line	KNX - Berker R.1/R.3/Serie 1930/R.classic
Secondary design line(s)	KNX, Berker R.1, Berker R.3, Serie 1930, Series R.classic

#### Instructions

- Use only in conjunction with bus coupling unit 8004 00 01!