

Berker TS



181112



Push-button, NO contact Berker TS, gold glossy, 24-carat galvanised

Technical features

| | nite | | |
|--|------|--|--|
| | | | |
| | | | |
| | | | |

| rediffical reactives | |
|--|--------------------------|
| Architecture | |
| Type of control unit | Push button |
| Configuration | |
| - Normally open contact | |
| Main electrical features | |
| Nominal voltage | 12 V |
| Rated voltage | 12 V |
| | |
| Electric current | |
| Momentary-contact current | 1,5 A |
| | |
| Materials | |
| Colour of design line | gold |
| Colour | gold |
| Colour | gold optics |
| RAL colour | RAL 1004 - Golden yellow |
| Material / workmanship | 24-carat galvanised |
| Material | brass |
| Surface appearance | glossy |
| - brass, refined | |
| Dimensions | |
| Depth | 19,7 mm |
| Insertion depth | 13 mm |
| Height | 22 mm |
| Width | 22 mm |
| Installation, mounting | |
| Installation mode | for screw fastening |
| Connection | |
| - with plug-in terminals | |
| with plag in terminals | |
| Safety | |
| Protection index IP | IP20 |
| Use conditions | |
| Operating temperature | -2060 °C |
| | |
| and the state of t | |

Identification Main design line



Instructions

- For connection via system interfaces to radio bus, KNX radio or KNX installations.

Alternatively, can be used to control relay circuits.