



75341104

Blind actuator flush-mounted 230 V AC KNX, light grey

Technical features

Architecture

Bus system	KNX
Fixing mode	flush-mounting

Functions

Bus module detachable	no
Operating mode	Operating mode can be set for blind, roller shutter/awning or ventilation flap

- suitable to switch different external conductors
- with safety functions e.g. for wind, rain, alarm
- with positioning function for blind and lamella position
- with sun shade function

Controls and indicators

- for activation of a drive for alternating current
- 2 buttons for manual operation and programming

Connectivity

Bus system radio frequent	no
Bus system LON	no
Bus system Powernet	no

Main electrical features

Frequency	50/60 Hz
-----------	----------

Voltage

Max. switching capacity at	230 V AC
Operating voltage over bus	21...32 V DC
System supply voltage	30V DC via bus

Electric current

Switching current at $\cos \varphi = 0.8$	max. 4 A
---	----------

Power

Switching capacity for max. 1 motor	600 VA
-------------------------------------	--------

Materials

Colour independent of design lines	light grey
------------------------------------	------------

Dimensions

Dimensions (\varnothing x H)	53 x 29 mm
Diameter	53 mm
Height	47,3 mm

LED control

LED	with 2 status LEDs for up/down, with red programming LED
-----	--

Connection

Conductor cross-section (flexible)	0,75...2,5 mm ²
Conductor cross-section (rigid)	0,75...2,5 mm ²
- with integral bus coupling unit	
- with screw terminals	
- bus connection via connecting terminal	

Settings

Supported configuration modes	system
- switching time on change of direction adjustable	

Scope of delivery

Bus connection included	yes
-------------------------	-----

Accessories included

- installation in flush-mounted or splash-protected junction box

Equipment

Modular expandability	no
-----------------------	----

Safety

Protection index IP	IP20
Halogen free	no

Use conditions

Operating temperature	-5...45 °C
Storage/transport temperature	-20...70 °C

Identification

Main design line	KNX
------------------	-----