




75311112



IP20



## Universal dim actuator 1gang pro RMD 600 W KNX, light grey

### Technical features

#### Architecture

Bus system	yes
Fixing mode	REG

#### Functions

Bus module detachable	no
<ul style="list-style-type: none"> <li>- suitable to switch different external conductors</li> <li>- Learning function for optimised operation of compact fluorescent lamps and LED luminaires can be activated via the bus</li> <li>- bulb-preserving soft startup</li> </ul>	

#### Controls and indicators

With LED indication	yes
Indicator lamp	yes
<ul style="list-style-type: none"> <li>- manual operation also possible without bus, e.g. on building site</li> <li>- Manual operation can be activated via selection switch, thereby deactivation of the KNX function</li> <li>- Manual operation per channel via button with integrated status LED, thereby lockout of KNX function</li> <li>- status LED integrated in the manual operation button</li> <li>- selection switch for manual/bus operation as well as load setting</li> <li>- with illuminated programming button</li> </ul>	

#### Connectivity

Bus system radio frequent	no
Bus system LON	no
Bus system Powernet	no

#### Main electrical features

Frequency	50/60 Hz
Rated current	4 mA

#### Voltage

Auxiliary voltage	230 V AC
Input voltage	230 V AC
Operating voltage over bus	21...32 V DC

#### Electric current

Bus current consumption (data transfer)	2,3 mA
---	--------

#### Fuse

Fuse	short-circuit proof and overload proof (display using LEDs), overheating protection (display using LEDs)
------	--

#### Power

Incandescent bulb power	600 W
Total power loss under IN	320 mW
Power dissipation per coil	180 mW

### Power supply

Supply voltage	230 V AC
----------------	----------

### Materials

Colour	light grey
--------	------------

### Dimensions

Width of rail mounted device (RMD)	4 modules
------------------------------------	-----------

### Fluorescent bulbs control

Power lighting fluo lamps	60W
---------------------------	-----

### LED control

Max number of LED/CFL lamps	8
-----------------------------	---

Power LED	60 W
-----------	------

LED	Status LED integrated in manual operation button, Overheating protection, display using LEDs, Overload protection, display via LED
-----	--

### Connection

Connection cross-sect. flexible conductor	0,75 / 2,5mm <sup>2</sup>
---	---------------------------

Connection cross-sect. rigid cable	0,75 / 2.5mm <sup>2</sup>
------------------------------------	---------------------------

Type of load	universal
--------------	-----------

Conductor cross-section (flexible)	0,75...2,5 mm <sup>2</sup>
------------------------------------	----------------------------

Conductor cross-section (rigid)	0,75...2,5 mm <sup>2</sup>
---------------------------------	----------------------------

Type of connection	quick connect
--------------------	---------------

- with integral bus coupling unit
- with QuickConnect plug-in terminals
- bus connection via connecting terminal

### Settings

Supported configuration modes	system
-------------------------------	--------

- parameter definable behaviour in the event of bus voltage failure/return

### Scope of delivery

Bus connection included	yes
-------------------------	-----

### Equipment

Type of dimmer	dimming actuator
----------------	------------------

Modular expandability	no
-----------------------	----

With slide for manual switch	yes
------------------------------	-----

- phase cut-on or cut-off according to load type, self-learning
- minimum/maximum dimming values per channel settable on device
- very low noise

### Use

Local operation/hand operation	yes
--------------------------------	-----

---

**Safety**

---

Protection index IP	IP20
Halogen free	no
- with overheating, overload and short-circuit protection	

---

**Use conditions**

---

Operating temperature	-5...45 °C
Storage/transport temperature	-20...70 °C

---

**Identification**

---

Main design line	KNX
------------------	-----

---