



85121100



ε



IP20

## Switch insert 1gang Electronics platform

### Technical features

### Functions

- bulb-preserving soft startup

### Main electrical features

Frequency 50/60 Hz

### Voltage

Operating voltage 230 V AC

### Fuse

Fuse short-circuit and overload proof (electronic fuse)

### Power

Dimmable conventional transformers 25...400 VA

Power consumption, standby (Channel 1/Channel 2) < 0.3/0.7 W

Power consumption (standby) < 0,3 W

Electronic transformers and dual-mode transformers 25...400 W

### Measurement

Relative humidity (without condensation) 0...65 % (without condensation)

Extension unit input with extension unit input for push-button (NO contact), single-surface operation and motion detector extension unit

### Materials

Colour not applicable

Material Plastic/metal

- no conductive connection between supporting ring and spreading claws

### Dimensions

Insertion depth 32 mm

### Fluorescent bulbs control

Dimmable energy-saving lamps 13...80 W

### LED control

Dimmable 230 V retrofit LED lamps 5...70 W

### Incandescent bulbs control

230 V incandescent lamps and halogen lamps 25...400 W

### Installation, mounting

Installation mode with spreader claws

### Connection

Screw terminals (max.)	2 x 1,5/1 x 2,5 mm <sup>2</sup>
Number of substations	unlimited
- with screw terminals	

### Cable

Load cable length	max. 100 m
Cable length, extensions	max. 50 m

### Settings

- Optimisation of the dimming performance by fine adjustment of the load type and special adjustment mode

### Equipment

- automatic setting of load-dependent switching principle (autoDetect process)

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	Light control, Motion detector, KNX radio-operating systems
Main design line	Electronics platform

### Instructions

Information text	Only suitable for operation with dimmable loads!
- Caution! Only connect dimmable 230 V ESL or retrofit-LED lamps.	