



85241131



IP20

## Blind button Berker R.1/R.3/R.8/Serie 1930/R.classic, black glossy

### Technical features

### Functions

Venetian blind movement time	2 mn
Running time	max. 2 mn
- Memory function for automatic execution of learned up and down times with position	
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)	

### Controls and indicators

- activation of the party function using buttons in up and down direction > 20 sec.

### Main electrical features

Nominal voltage	12 V
Frequency	- Hz

### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

### Materials

Colour of design line	black
Colour	black
Material	thermoplastic

### Dimensions

Diameter	57,6 mm
----------	---------

### LED control

LED	LED application module/insert compatibility display, with status LED for memory and party function, red/orange, with indicator LED for lock-out protection
-----	--

### Installation, mounting

Installation mode	clamp fastening
-------------------	-----------------

### Settings

Lamella adjusting time	(adjustable) 50 ms...2,5 s
Minimum slat adjustment time	≈ 250 ms
Delay time, adjustable	0...500 s
Lamella adjustment on button-press	< 0,4 s

### Equipment

Self-retaining for 2 min on button-press	> 0,4 s
Change-over time for change of direction	< 0,6 s

### Safety

- with dismantling protection

---

**Use conditions**

---

Operating temperature -5...45 °C

---

- low intrinsic energy requirement

---

**Identification**

---

Application, usage Blind control

---

Main design line Berker R.1/R.3/R.8/Serie 1930/R.classic

---

Secondary design line(s) Electronics platform, Berker R.1, Berker R.3, Berker R.8

---

**Instructions**

---

- Can be switched to orientation led by extension unit.
  - Note:  
When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!
-