



**Neon lamp unit with N terminal Light control, orange**

Technical features

**Architecture**

Technical version 230 V~, 0.4 mA

**Controls and indicators**

- for rocker push-buttons and multiple rockers push-buttons, except order no. 503404, 503808
- for change-over/intermediate switch and on/off switch, 2-pole, 10 AX

**Main electrical features**

Rated current 0,4 mA

**Materials**

Colour independent of design lines orange

**Dimensions**

Insertion depth 13 mm

**Equipment**

- for lighting and monitoring circuit
- for series switch illuminated

**Identification**

Application, usage Light control

Main design line Light control

Secondary design line(s) Light control, ACCESSORIES

**Instructions**

Information text

When several neon lamp units are used, the lamp current may result in malfunctioning of the relay/pulse relay.  
Remedy: Carry along a neutral conductor or connect a capacitor 230 V (1 µF per 10 mA neon lamp current) in parallel with the coil.

- Refer to the overview for the matching flush-mounted inserts.
- these marked articles (see symbol) are only suitable for the water-protected flush-mounted installation IP44 in conjunction with the corresponding seal, frame and contact protection box (imprint "IP44").

167504

