



16406096



## Relay switch with centre plate for hotel card Berker Q.1/Q.3/Q.7/Q.9, anthracite velvety

### Technical features

#### Architecture

Fixing mode	flush-mounting
-------------	----------------

#### Configuration

- 1pole
---------

#### Main electrical features

Nominal voltage	230 V
Rated voltage	230 V AC
Frequency	50/60 Hz

#### Electric current

Inductive load at $\cos \varphi = 0.6$	max. 6 A
Switching current	10 A /230 V AC1

#### Power

Conventional transformers	1500 VA
Electronic transformers	1500 W
Power consumption	< 0.2 W

#### Materials

Colour of design line	anthracite
Colour	anthracite
Colour	anthracite charcoal grey
RAL colour	RAL 7021 - Black grey
Material / workmanship	lacquered
Material	Plastic/metal
Surface appearance	velvety

#### Dimensions

Depth	57,3 mm
Insertion depth	32 mm
Card width	max. 55 mm
Card thickness	0,8...1,2 mm
Height	71 mm
Width	71 mm

#### Fluorescent bulbs control

Compact fluorescent lamps	500 W
Fluorescent lamps in duo circuit	1500 W

#### LED control

LED	illuminated with blue LED if hotel card is not inserted
-----	---

---

**Incandescent bulbs control**

---

230 V incandescent lamps and halogen lamps	1500 W
--	--------

---

**Installation, mounting**

---

Installation mode	with spreader claws
-------------------	---------------------

---

**Connection**

---

Screw terminals (max.)	2 x 2,5 mm <sup>2</sup>
------------------------	-------------------------

---

- with screw-in lift terminals

---

**Settings**

---

Delay time incrementally adjustable	0, 15, 30, 60 s
-------------------------------------	-----------------

---

- with potentiometer for incremental adjustment of delay time

---

**Equipment**

- 
- for illumination
  - with potential-free contact
- 

**Safety**

---

Protection index IP	IP20
---------------------	------

---

**Use conditions**

---

Operating temperature	-5...50 °C
Storage/transport temperature	-25...70 °C (storage at > 45°C reduces the service life)

---

**Identification**

---

Application, usage	Light control
Main design line	Berker Q.1/Q.3/Q.7/Q.9
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

---