



47086086



**SCHUKO socket outlet with residual current circuit-breaker enhanced contact protection, Berker Q.1/Q.3/Q.7/Q.9, anthracite velvety, lacquered**

Technical features

#### Architecture

Design	according to DIN 49440
Fixing mode	flush-mounting
- type A for alternating currents and pulsating direct currents	

#### Main electrical features

Nominal voltage	250 V
Rated voltage	250 V AC
Frequency	50/60 Hz
Rated current	16 A

#### Electric current

Measurement error current	30 mA
Rated current	16 A
Surge current resistance	250 A
Short-circuit resistance (with back-up fuse 20 AgL)	3 kA

#### Tripping

Trigger time	30 ms
--------------	-------

#### Cover, door

Cover	Central cover plate
-------	---------------------

#### Materials

Colour of design line	anthracite
Colour	anthracite
Colour	anthracite charcoal grey
RAL colour	RAL 7021 - Black grey
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	velvety

#### Dimensions

Insertion depth	31,9 mm
-----------------	---------

#### Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

#### Connection

Connection terminals	according to IEC 60884-1
Connection terminals	according to VDE 0620-1:2021-02
- with plug-in terminals	

---

**Use**

---

Differentiation characteristic 2 - Sales	enhanced contact protection
--	-----------------------------

---

**Standards**

---

Tested	conform VDE 0664 (EN 61008)
--------	-----------------------------

---

**Safety**

---

IK protection code against mechanical impacts	02
---	----

---

Protection index IP	IP20
---------------------	------

---

Enhanced contact protection	according to IEC 60884-1
-----------------------------	--------------------------

---

Enhanced contact protection	according to VDE 0620-1:2021-02
-----------------------------	---------------------------------

---

- Enhanced contact protection	
-------------------------------	--

---

**Identification**

---

Main design line	Berker Q.1/Q.3/Q.7/Q.9
------------------	------------------------

---

Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9
--------------------------	--

---