



41096086



**SCHUKO socket outlet with LED orientation light enhanced contact protection, Screw-in lift terminals, Berker Q.1/Q.3/Q.7/Q.9, anthracite velvety, lacquered**

Technical features

#### Architecture

Design	according to DIN 49440
Fixing mode	flush-mounting

#### Main electrical features

Nominal voltage	250 V
Rated voltage	250 V AC
Frequency	50/60 Hz
Rated current	16 A

#### Electric current

Rated current	16 A
---------------	------

#### Power

Power consumption	0.25 W/0.35 VA
-------------------	----------------

#### Cover, door

Cover	Central cover plate
-------	---------------------

#### Detection

- integrated brightness sensor that switches the orientation light on at twilight and off when there is sufficient brightness

#### Materials

Colour of design line	anthracite
Colour	anthracite
Colour	anthracite charcoal grey
RAL colour	RAL 7021 - Black grey
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	velvety

#### Dimensions

Insertion depth	32 mm
-----------------	-------

#### Lighting control

Switch-off brightness	≈ 4 lx
Switch-on brightness	≈ 2 lx
Light intensity (white)	0,2 cd

#### LED control

LED	white LED light, long service life of the LED
-----	---

### Installation, mounting

Installation mode with spreader claws

### Connection

Conductor cross-section (rigid) max. 2,5 mm<sup>2</sup>

Connection terminals according to IEC 60884-1

Connection terminals according to VDE 0620-1:2021-02

- with screw-in lift terminals

### Cable

- through-wiring possible, therefore also ideal for retrofitting

### Equipment

- additional benefit by combination of a socket outlet with an orientation light

### Use

Differentiation characteristic 2 - Sales enhanced contact protection

Differentiation characteristic 3 - Sales Screw-in lift terminals

### Safety

IK protection code against mechanical impacts 05

Protection index IP IP20

Enhanced contact protection according to IEC 60884-1

Enhanced contact protection according to VDE 0620-1:2021-02

- Enhanced contact protection

### Identification

Main design line Berker Q.1/Q.3/Q.7/Q.9

Secondary design line(s) Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

### Instructions

Information text Caution!  
Items with special flush-mounted insert.  
Centre plates with LED orientation lights are not compatible with the standard socket outlets.