



85146182



IP20

## KNX radio button 2gang quicklink Berker S.1/B.3/B.7, white glossy

### Technical features

#### Functions

- ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
- Configurable transmission and/or reception behaviour
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- scene saving lockable
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

#### Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration and function button

#### Connectivity

Radio protocol	KNX Radio
Receiver category	2

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

#### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

#### Materials

Colour of design line	white
RAL colour	RAL 1013 - Oyster white
Material	thermoplastic
Surface appearance	glossy

#### LED control

LED	with configuration and function LEDs, LED application module/insert compatibility display
-----	---

#### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

#### Settings

- top and bottom operating areas on 2gang switching/dimming inserts and network insert are freely configurable
- toolless quicklink configuration using buttons and LED display

#### Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %
- switch-on brightness level for each operating area on configuration with dimmer insert, power failure proof, storable	

#### Safety

- with dismantling protection

#### Use conditions

- |                                    |            |
|------------------------------------|------------|
| Operating temperature              | -5...45 °C |
| - low intrinsic energy requirement |            |

#### Identification

- |                          |  |
|--------------------------|--|
| Application, usage       | Light control, KNX radio- operating systems              |
| Main design line         | Berker S.1/B.3/B.7                                       |
| Secondary design line(s) | Electronics platform, Berker S.1, Berker B.3, Berker B.7 |