




85745288



## KNX radio timer quicklink with display, Berker S.1/B.3/B.7, polar white matt

### Technical features

#### Functions

Astronomic time shift	± 2 h
Random number generator	± 15 mn
Power reserve	≈ 24 h

- ETS additional functions: +6 scenes, operating mode on/off, scene loading, time dimming value, push-button, status display
- reset function (to factory setting)
- Configurable transmission and/or reception behaviour
- Party function, no execution of automatic, radio and extension unit commands (switch protection)
- with keylock
- easy additional functions: +6 scenes, dimming, 1 up/down button control, priority
- quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control
- with switchover manual/automatic mode

#### Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

#### Connectivity

Radio protocol	KNX Radio
----------------	-----------

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

#### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
Running accuracy	± 3 min/year

#### Materials

Colour of design line	polar white
Surface appearance	matt

#### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

#### Settings

Time	with automatic summer-/winter time switching (can be switched off)
------	--

- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- standalone programme, radio and extension unit commands are not executed
- holiday programme for random variation of the switching times in automatic operation

#### Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Number of switching times for on/off	20

- 2 independent preset programme memories, individually adaptable

---

**Use**

---

Differentiation characteristic 2 - Sales with display

---

**Safety**

---

Protection index IP IP20

---

- with dismantling protection

---

**Use conditions**

---

Operating temperature -5...45 °C

---

- low intrinsic energy requirement

---

**Identification**

---

Application, usage Light control, KNX radio- operating systems

---

Main design line Berker S.1/B.3/B.7

---

Secondary design line(s) Electronics platform, Berker S.1, Berker B.3, Berker  
B.7

---