



85341285



IR motion detector comfort 1.1 m Berker S.1/B.3/B.7, anthracite, matt

Technical features

Architecture

Fixing mode	flush-mounting
-------------	----------------

Functions

Operating mode	step operation with immunity time (e.g. for stair light/impact current circuits)
----------------	--

- μ -processor controlled mode of operation
- Teach function for response brightness via button
- with keylock
- Party function for switching on for 2 hours
- with memory function for presence simulation

Controls and indicators

- with button for on/off/automatic

Tripping

immunity time	≈ 10 s
---------------	----------------

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
Detection field, rectangular shaped	$\approx 12 \times 16$ m

Reach distance

Range, frontal	≈ 12 m
Range, side	each ≈ 8 m

Detection

Number of detection levels	3
Detection angle, settable	each side $\approx 45...90^\circ$

Materials

Colour of design line	anthracite
Colour	anthracite
Material	thermoplastic

Dimensions

Assembling height	34 mm
Nominal mounting height	1,1 m

Lighting control

Response brightness, adjustable	$\approx 5...1000$ lx , daytime operation
---------------------------------	---

LED control

LED	with operation and status LED, red/green/orange, LED application module/insert compatibility display
-----	--

Settings

Response value luminosity adjustable	yes
Response value sensitivity adjustable	yes
Response sensitivity, settable	10...100 %
Short time mode	200 ms
Delay time	≈ 180 s
Delay time, adjustable	≈ 10 s...30 mn
Switch-off pre-warning to dimming value 50% for	30 s

Safety

Protection index IP	IP20
- with dismantling protection	

Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

Identification

Application, usage	Light control, Motion detector
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Motion detector, Berker S.1, Berker B.3, Berker B.7

Instructions

Information text	Continuous direct sunlight penetrating the upward-pointing detection plane can result in failure of the motion detector. Only suitable for indoor areas!
------------------	---