



286710



## Tronic rotary dimmer 360 W (R, C) Light control, others

### Technical features

#### Functions

- bulb-preserving soft startup

#### Main electrical features

Nominal voltage	230 V
Frequency	50 Hz

#### Voltage

Operating voltage	230 V AC
-------------------	----------

#### Fuse

Fuse	short-circuit and overload proof (electronic fuse)
------	--

#### Power

Electronic transformers	20...360 W
-------------------------	------------

#### Materials

Colour	not applicable
Material	Plastic/metal

#### Dimensions

Axis dimension Ø	4 mm
------------------	------

#### Incandescent bulbs control

230 V incandescent lamps and halogen lamps	20...360 W
--	------------

#### Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

#### Connection

Type of load	capacitive
- with screw terminals	

#### Equipment

- phase cut-off
- very low noise
- with change-over pressure switch

#### Safety

Halogen free	yes
--------------	-----

#### Identification

Application, usage	Light control
Main design line	Light control

#### Instructions

Information text

Trouble-free operation will be obtained only with  
Berker TronicÂ® transformers.