



286710



Tronic rotary dimmer 360 W (R, C) Light control, others

Technical features

Functions

- bulb-preserving soft startup

Main electrical features

| | |
|-----------------|-------|
| Nominal voltage | 230 V |
| Frequency | 50 Hz |

Voltage

| | |
|-------------------|----------|
| Operating voltage | 230 V AC |
|-------------------|----------|

Fuse

| | |
|------|--|
| Fuse | short-circuit and overload proof (electronic fuse) |
|------|--|

Power

| | |
|-------------------------|------------|
| Electronic transformers | 20...360 W |
|-------------------------|------------|

Materials

| | |
|----------|----------------|
| Colour | not applicable |
| Material | Plastic/metal |

Dimensions

| | |
|------------------|------|
| Axis dimension Ø | 4 mm |
|------------------|------|

Incandescent bulbs control

| | |
|--|------------|
| 230 V incandescent lamps and halogen lamps | 20...360 W |
|--|------------|

Installation, mounting

| | |
|-------------------|---------------------|
| Installation mode | with spreader claws |
|-------------------|---------------------|

Connection

| | |
|------------------------|------------|
| Type of load | capacitive |
| - with screw terminals | |

Equipment

- phase cut-off
- very low noise
- with change-over pressure switch

Safety

| | |
|--------------|-----|
| Halogen free | yes |
|--------------|-----|

Identification

| | |
|--------------------|---------------|
| Application, usage | Light control |
| Main design line | Light control |

Instructions

Information text

Trouble-free operation will be obtained only with
Berker TronicÂ® transformers.