



85122200



IP20

## Switch insert 2gang Electronics platform

### Technical features

### Functions

- bulb-preserving soft startup

### Main electrical features

Frequency 50/60 Hz

### Voltage

Operating voltage 230 V AC

### Fuse

Fuse short-circuit and overload proof (electronic fuse)

### Power

Dimmable conventional transformers per channel 35...300 VA

Power consumption, standby (Channel 1/Channel 2) < 0.3/0.7 W

Electronic transformers and dual-mode transformers per channel 35...300 W

### Measurement

Relative humidity (without condensation) 0...65 % (without condensation)

Extension unit input with 2 extension unit inputs for push-button (NO contact), single-surface operation

### Materials

Colour not applicable

Material Plastic/metal

- no conductive connection between supporting ring and spreading claws

### Dimensions

Insertion depth 32 mm

### Fluorescent bulbs control

Dimmable energy-saving lamps per channel 15...54 W

### LED control

Dimmable 230 V retrofit LED lamps per channel 12...54 W

### Incandescent bulbs control

230 V incandescent lamps and halogen lamps per channel 35...300 W

### Installation, mounting

Installation mode with spreader claws

#### Connection

Screw terminals (max.)	2 x 1,5/1 x 2,5 mm <sup>2</sup>
Number of substations	unlimited
- with screw terminals	

#### Cable

Load cable length	max. 100 m
Cable length, extensions	max. per channel 50 m

#### Settings

- Optimisation of the dimming performance by fine adjustment of the load type and special adjustment mode

#### Equipment

- automatic setting of load-dependent switching principle (autoDetect process)

#### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

#### Identification

Application, usage	Motion detector, KNX radio- operating systems, Light control
Main design line	Electronics platform

#### Instructions

Information text	Only suitable for operation with dimmable loads!
- Caution! Only connect dimmable 230 V ESL or retrofit-LED lamps.	