



85648122



IP20

KNX radio button 4gang quicklink Berker Q.1/Q.3/Q.7/Q.9

Technical features

Functions

- ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
- Functions for the push-button operation areas up/down or left/right can be freely configured as receiver for controlling the connected load and as transmitter for remote control of a blind, for example
- reset function (to factory setting)
- Configurable transmission and/or reception behaviour
- scene saving lockable
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration and function button

Connectivity

Radio protocol	KNX Radio
Receiver category	2

Power

Radio transmission power	< 10 mW
--------------------------	---------

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

Materials

Colour of design line	white
RAL colour	RAL 1013 - Oyster white
Material	thermoplastic
Surface appearance	velvety

LED control

LED	with configuration and function LEDs, LED application module/insert compatibility display
-----	---

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

- toolless quicklink configuration using buttons and LED display

Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

- switch-on brightness level for each operating area on configuration with dimmer insert, power failure proof, storable

Safety

- with dismantling protection

Use conditions

Operating temperature

-5...45 °C

- low intrinsic energy requirement

Identification

Application, usage

Light control, KNX radio- operating systems

Main design line

Berker Q.1/Q.3/Q.7/Q.9

Secondary design line(s)

Electronics platform, Berker Q.1, Berker Q.3, Berker
Q.7, Berker Q.9

Instructions

Information text

Extended operating options on 1 gang inserts
through 2 additional, freely-configurable radio
channels.
