



85341124





Motion detector 1.1 m Berker Q.1/Q.3/Q.7/Q.9

Technical features

Architecture

Fixing mode flush-mounting

Functions

- μ-processor controlled mode of operation
- Teach function for response brightness via button
- with keylock
- Party function for switching on for 2 hours
- with memory function for presence simulation

Controls and indicators

- with button for on/off/automatic

Measurement

| Relative humidity (without condensation) | 065 % (without condensation) | | |
|--|------------------------------|--|--|
| Detection field, rectangular shaped | ≈ 12 x 16 m | | |

Reach distance

| Range, frontal | ≈ 12 m |
|----------------|------------|
| Range, side | each ≈ 8 m |

Detection

| Number of detection levels | 3 |
|----------------------------|--------------------|
| Detection angle, settable | each side ≈ 4590 ° |

Materials

| Colour of design line | aluminium | |
|------------------------|---------------|--|
| Colour | aluminium | |
| Material / workmanship | lacquere | |
| Material | thermoplastic | |

Dimensions

| Assembling height | 34 mm |
|-------------------------|-------|
| Nominal mounting height | 1.1 m |

Lighting control

LED control

| LED | with operation and status LED, red/green/orange, |
|-----|---|
| | LED application module/insert compatibility display |



| ^ | | | | | | |
|---|---|---|---|---|---|---|
| S | Δ | п | П | n | n | с |
| | | | | | | |

| Settings | |
|---|---|
| Response value luminosity adjustable | yes |
| Response value sensitivity adjustable | yes |
| Response sensitivity, settable | 10100 % |
| Delay time | ≈ 180 s |
| Switch-off pre-warning to dimming value 50% for | 30 s |
| Safety | |
| Protection index IP | IP20 |
| - with dismantling protection | |
| Use conditions | |
| Operating temperature | -545 °C |
| - low intrinsic energy requirement | |
| Identification | |
| Application, usage | Light control, Motion detector |
| Main design line | Berker Q.1/Q.3/Q.7/Q.9 |
| Secondary design line(s) | Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9 |
| Instructions | |
| Information text | Continuous direct sunlight penetrating the upward- pointing detection plane can result in failure of the motion detector. |
| | Only suitable for indoor areas! |