



85341283



**IR motion detector comfort 1.1 m Berker S.1/B.3/B.7, aluminium, matt, lacquered**

Technical features

**Architecture**

Fixing mode flush-mounting

**Functions**

Operating mode step operation with immunity time (e.g. for stair light/impact current circuits)

- $\mu$ -processor controlled mode of operation
- Teach function for response brightness via button
- with keylock
- Party function for switching on for 2 hours
- with memory function for presence simulation

**Controls and indicators**

- with button for on/off/automatic

**Tripping**

immunity time  $\approx 10$  s

**Measurement**

Relative humidity (without condensation) 0..65 % (without condensation)

Detection field, rectangular shaped  $\approx 12 \times 16$  m

**Reach distance**

Range, frontal  $\approx 12$  m

Range, side each  $\approx 8$  m

**Detection**

Number of detection levels 3

Detection angle, settable each side  $\approx 45..90^\circ$

**Materials**

Colour of design line aluminium

Colour aluminium

Material / workmanship lacquered

Material thermoplastic

**Dimensions**

Assembling height 34 mm

Nominal mounting height 1,1 m

**Lighting control**

Response brightness, adjustable  $\approx 5..1000$  lx , daytime operation

**LED control**

LED with operation and status LED, red/green/orange, LED application module/insert compatibility display

### Settings

Response value luminosity adjustable	yes
Response value sensitivity adjustable	yes
Response sensitivity, settable	10...100 %
Short time mode	200 ms
Delay time	≈ 180 s
Delay time, adjustable	≈ 10 s...30 mn
Switch-off pre-warning to dimming value 50% for	30 s

### Safety

Protection index IP	IP20
- with dismantling protection	

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	Light control, Motion detector
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Motion detector, Berker S.1, Berker B.3, Berker B.7

### Instructions

Information text	Continuous direct sunlight penetrating the upward-pointing detection plane can result in failure of the motion detector. Only suitable for indoor areas!
------------------	---