


2874



## Tronic rotary dimmer 525 W (R, C) with soft-lock, Light control, others

### Technical features

#### Functions

- bulb-preserving soft startup

#### Main electrical features

Nominal voltage	230 V
Frequency	50 Hz

#### Voltage

Operating voltage	230 V AC
- voltage test possible without dismantling	

#### Fuse

Fuse	short-circuit and overload proof (electronic fuse)
------	--

#### Power

Loss power at full load	≈ 5 W
Electronic transformers	20...525 W

#### Materials

Colour	not applicable
Material	Plastic/metal

#### Dimensions

Axis dimension Ø	4 mm
------------------	------

#### Incandescent bulbs control

230 V incandescent lamps and halogen lamps	20...525 W
--	------------

#### Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

#### Connection

Type of load	capacitive
- with terminal for base load from mains isolator	
- with plug-in terminals	

#### Equipment

- phase cut-off
- very low noise
- with change-over pressure switch

#### Use

Differentiation characteristic 3 - Sales	with soft-lock
--	----------------

---

**Safety**

---

Halogen free	yes
--------------	-----

---

**Identification**

---

Application, usage	Light control
--------------------	---------------

---

Release issue	2
---------------	---

---

Main design line	Light control
------------------	---------------

---

**Instructions**

---

Information text	Trouble-free operation will be obtained only with Berker TronicÂ® transformers.
------------------	--

---