


2874



Tronic rotary dimmer 525 W (R, C) with soft-lock, Light control, others

Technical features

Functions

- bulb-preserving soft startup

Main electrical features

Nominal voltage	230 V
Frequency	50 Hz

Voltage

Operating voltage	230 V AC
- voltage test possible without dismantling	

Fuse

Fuse	short-circuit and overload proof (electronic fuse)
------	--

Power

Loss power at full load	≈ 5 W
Electronic transformers	20...525 W

Materials

Colour	not applicable
Material	Plastic/metal

Dimensions

Axis dimension Ø	4 mm
------------------	------

Incandescent bulbs control

230 V incandescent lamps and halogen lamps	20...525 W
--	------------

Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

Connection

Type of load	capacitive
- with terminal for base load from mains isolator	
- with plug-in terminals	

Equipment

- phase cut-off
- very low noise
- with change-over pressure switch

Use

Differentiation characteristic 3 - Sales	with soft-lock
--	----------------

Safety

Halogen free	yes
--------------	-----

Identification

Application, usage	Light control
--------------------	---------------

Release issue	2
---------------	---

Main design line	Light control
------------------	---------------

Instructions

Information text	Trouble-free operation will be obtained only with Berker TronicÂ® transformers.
------------------	--
