



85656239



**KNX radio wall-transmitter 2gang flat quicklink Berker R.1/R.3/R.8/Serie 1930/R.classic, polar white glossy**

Technical features

**Functions**

- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

**Controls and indicators**

- operating areas configurable as one or two-area operation
- with configuration button

**Connectivity**

Radio protocol	KNX Radio
Receiver category	2

**Frequency**

Radio transmission frequency	868,3 MHz
------------------------------	-----------

**Power**

Radio transmission power	< 10 mW
--------------------------	---------

**Measurement**

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

**Battery**

Battery service life [years]	≈ 5
- with lithium coin cell battery 3 V type: CR 2430	

**Materials**

Colour of labelling	105,105,105
Colour of design line	polar white
RAL colour	RAL 9010 - Pure white
Material	thermoplastic
Material for printing	ASA polar white
Surface appearance	glossy

**Dimensions**

Assembling height	14 mm
-------------------	-------

**LED control**

LED	with configuration LED, with transmission status and battery status LED, red/green/orange
-----	---

**Installation, mounting**

Installation mode	for flat surface mounting and extension of combinations
-------------------	---

### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Settings

- toolless quicklink configuration using buttons and LED display
- top and bottom operating areas are freely configurable

### Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Type of configuration	Laserdruck
Transmitter duty cycle	1 %

### Safety

- with dismantling protection

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	KNX radio- operating systems
Main design line	Berker R.1/R.3/R.8/Serie 1930/R.classic
Secondary design line(s)	Electronics platform, Berker R.1, Berker R.3, Berker R.8, Series R.classic, Serie 1930