



85146139



IP20

## KNX radio button 2gang quicklink Berker R.1/R.3/R.8/Serie 1930/R.classic, polar white glossy

### Technical features

#### Functions

- ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
- Configurable transmission and/or reception behaviour
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- scene saving lockable
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

#### Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration and function button

#### Connectivity

Radio protocol	KNX Radio
Receiver category	2

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

#### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

#### Materials

Colour of labelling	105,105,105
Colour of design line	polar white
RAL colour	RAL 9010 - Pure white
Material	thermoplastic
Material for printing	ASA polar white
Surface appearance	glossy

#### LED control

LED	with configuration and function LEDs, LED application module/insert compatibility display
-----	---

#### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

#### Settings

- top and bottom operating areas on 2gang switching/dimming inserts and network insert are freely configurable
- toolless quicklink configuration using buttons and LED display

### Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Type of configuration	Laserdruck
Transmitter duty cycle	1 %
- switch-on brightness level for each operating area on configuration with dimmer insert, power failure proof, storable	

### Safety

- with dismantling protection

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	Light control, KNX radio- operating systems
Main design line	Berker R.1/R.3/R.8/Serie 1930/R.classic
Secondary design line(s)	Electronics platform, Berker R.1, Berker R.3, Serie 1930, Series R.classic

### Instructions

- Note:  
When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!