



85741173



IP20

## Blind time switch with display, Berker K.5, stainless steel matt, lacquered

### Technical features

### Functions

Astronomic time shift	± 2 h
Running time	2 mn
Random number generator	± 15 mn
Power reserve	≈ 24 h
<ul style="list-style-type: none"> <li>- reset function (to factory setting)</li> <li>- with keylock</li> <li>- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)</li> <li>- with switchover manual/automatic mode</li> </ul>	

### Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

### Main electrical features

Nominal voltage	12 V
Frequency	- Hz

### Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

### Detection

- Not suitable for rain and wind sensors

### Materials

Colour of design line	stainless steel
Colour	stainless steel
Material / workmanship	lacquered
Material	Plastic/metal

### Installation, mounting

Installation mode	clamp fastening
-------------------	-----------------

### Settings

Minimum slat adjustment time	≈ 250 ms
Lamella adjustment on button-press	< 0,5 s
Time	with automatic summer-/winter time switching (can be switched off)
<ul style="list-style-type: none"> <li>- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable</li> <li>- holiday programme for random variation of the operation times in automatic operation</li> </ul>	

### Equipment

Number of operation times for up/down	20
Self-retaining for 2 min on button-press	> 0,5 s
Change-over time for change of direction	< 0,6 s
- 2 independent preset programme memories, individually adaptable	

### Use

Differentiation characteristic 2 - Sales	with display
--	--------------

### Safety

- with dismantling protection

### Use conditions

Operating temperature	-5...45 °C
- low intrinsic energy requirement	

### Identification

Application, usage	Blind control
Main design line	Berker K.5
Secondary design line(s)	Electronics platform, Berker K.5

### Instructions

- Can be switched to orientation led by extension unit.