

± 50 %



75261652



IP20

KNX controller comfort 2.2 m KNX - Berker S.1, white glossy

Technical features

Architecture

Fixing mode	flush-mounting
Functions	
Max. temporisation	306 h

- Potentiometer for additional delay time
 Functions for lighting operating mode: Switching, Value transmitter and Light scene call
- parameter defineable lock function
- with slide switch for OFF/automatic/ON

Compatibility

- also suitable as extension unit

Controls and indicators

Number of switching segments 72

Power

Power consumption, KNX ≈ 110 mW

Measurement

Detection field, semi-oval shaped $\approx 12 \times 12 \text{ m}$

Reach distance

Range, frontal	≈ 12 m
Range, frontal (at 1.1 m installation height)	≈ 6 m
Range, side	each ≈ 6 m
Range, side (at 1.1 m installation height)	each ≈ 3 m
Max. transmission range frontally	12 m
Max. transmission range sideways	6 m

Cover, door

Cover with cover to limit detection angle to 90°

Detection

Number of detection levels	2
Detection angle	180°
Detection angle vertical	0/7°
Detection angle horizontal	0 / 180 °
Sensor type	detector of movement

Materials

Colour of design line	white
RAL colour	RAL 1013 - Oyster white
Material	thermoplastic
Surface appearance	glossy



Dimensions	
Dimensions assembling height	23,5 mm
Nominal mounting height	2,2 m
Optimum mounting height	2,2 m
Lighting control	
Response brightness, configurable	3100 lx / daytime operation
LED control	
LED	with red diagnostic LED for brightness-independent walk test function and disassembly message
Connection	
- for bus coupling unit flush-mounted	
Settings	
Supported configuration modes	system
Response brightness adjustable by potentiometer	± 50 %
Response sensitivity, settable	20100 %
Min. temporisation	130 ms
Delay time	≈ 10 s
Additional delay time programmable	130 ms306 h
- with potentiometers for fine adjustment of the resp	oonse brightness, sensitivity and delay time
Equipment	
Product type:	product type: movement
- with lighting and message mode	
Safety	
Protection index IP	IP20
Halogen free	no
- alarm telegram after disconnection from bus coup	ling unit, 1-bit
Use conditions	
Operating temperature	-545 °C
Identification	
Application, usage	KNX - sensors
Product family	product family: physical sensors
Main design line	KNX - Berker S.1
Secondary design line(s)	Motion detector, KNX
Instructions	
Information text	Application as for order no. 7526 15
	Caution: Direct sunlight can lead to false alarms when using alarm application. Avoid using detection field
	equipment on windows.