


75318102



## Switch actuator/blind actuator 8/4gang pro RMD 4 A, with auxiliary voltage with plug-in terminals, KNX, light grey

### Technical features

### Architecture

Bus system	yes
Fixing mode	REG
Technical version	8/4gang, with Auxiliary voltage

### Functions

Operating mode	any combined operation from drive and switching functions possible
----------------	--

- suitable to switch different external conductors
- with positioning function for blind and lamella position
- with safety functions e.g. for wind, rain, alarm
- with sun shade function
- for switching, e.g. of 8 independent loads or activation of 4 drives

### Controls and indicators

Indicator lamp	yes
----------------	-----

- Manual operation can be activated via selection switch, thereby deactivation of the KNX function
- manual operation per channel using button (single-area operation)
- status LED integrated in the manual operation button
- manual operation buttons for on/off (up/down) and bus function on/off per channel/device
- with illuminated programming button

### Connectivity

Bus system radio frequent	no
Bus system LON	no
Bus system Powernet	no

### Main electrical features

Rated current	4 A
---------------	-----

### Voltage

Auxiliary voltage	230 V AC
Operating voltage over bus	21...32 V DC
Output voltage	230 V~
System supply voltage	30V DC via bus

### Electric current

Bus current consumption (data transfer)	15 mA
Bus current consumption (idle)	9 mA
Maximum through current	4 A
Switching current at $\cos \varphi = 0.8$	max. 4 A

#### Power

Max. power with electronic transfo.	800 W
Total power loss under IN	2 W
Output power	800 W
Conventional transformers	800 VA
Electronic transformers	800 W

#### Materials

Colour	light grey
--------	------------

#### Dimensions

Depth	65 mm
Width of rail mounted device (RMD)	6 modules
Height	90 mm
Width	105 mm

#### Lighting control

Fluorescent lamps with electronical ballast (EB)	12 x 36 W
- uncompensated	800 W

#### Fluorescent bulbs control

Energy-saving lamps	6 x 23 W
Power lighting fluo lamps	6x23W
Max. power fluo. duo lamp comp. series	12 x 36 W

#### LED control

Max number of LED/CFL lamps	6
230V LED lamps	6 x 23 W
Power LED	72 W
LED	Status LED integrated in manual operation button

#### Incandescent bulbs control

Max. power with incandescent lamps	800 W
230 V incandescent lamps	800 W
230 V halogen lamps	800 W
230 V incandescent lamps and halogen lamps	800 W

#### Connection

Connection cross-sect. flexible conductor	0,75 / 2,5mm <sup>2</sup>
Connection cross-sect. rigid cable	0,75 / 2.5mm <sup>2</sup>
Conductor cross-section (flexible)	0,75...2,5 mm <sup>2</sup>
Conductor cross-section (rigid)	0,75...2,5 mm <sup>2</sup>
Type of connection	quick connect
<ul style="list-style-type: none"> <li>- with integral bus coupling unit</li> <li>- with QuickConnect plug-in terminals</li> <li>- bus connection via connecting terminal</li> </ul>	

### Settings

Supported configuration modes	system
- switching time on change of direction adjustable	

### Scope of delivery

Bus connection included	yes
-------------------------	-----

### Equipment

Modular expandability	no
Different phases connectable	yes
With slide for manual switch	yes
- with potential-free NO contacts as well as NC contact parameterisable	

### Use

Differentiation characteristic 3 - Sales	with plug-in terminals
--	------------------------

### Safety

Protection index IP	IP20
---------------------	------

### Use conditions

Operating temperature	-5...45 °C
Storage/transport temperature	-20...70 °C

### Identification

Main design line	KNX
------------------	-----