



85146139



IP20

KNX radio button 2gang quicklink Berker R.1/R.3/R.8/Serie 1930/R.classic, polar white glossy

Technical features

Functions

- ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
- Configurable transmission and/or reception behaviour
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- scene saving lockable
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration and function button

Connectivity

Radio protocol	KNX Radio
Receiver category	2

Power

Radio transmission power	< 10 mW
--------------------------	---------

Measurement

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

Materials

Colour of labelling	105,105,105
Colour of design line	polar white
RAL colour	RAL 9010 - Pure white
Material	thermoplastic
Material for printing	ASA polar white
Surface appearance	glossy

LED control

LED	with configuration and function LEDs, LED application module/insert compatibility display
-----	---

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

- top and bottom operating areas on 2gang switching/dimming inserts and network insert are freely configurable
- toolless quicklink configuration using buttons and LED display

Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Type of configuration	Laserdruck
Transmitter duty cycle	1 %

- switch-on brightness level for each operating area on configuration with dimmer insert, power failure proof, storable

Safety

-
- with dismantling protection
-

Use conditions

Operating temperature	-5...45 °C
-----------------------	------------

- low intrinsic energy requirement

Identification

Application, usage	Light control, KNX radio- operating systems
Main design line	Berker R.1/R.3/R.8/Serie 1930/R.classic
Secondary design line(s)	Electronics platform, Berker R.1, Berker R.3, Serie 1930, Series R.classic

Instructions

-
- Note:
When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!
-