



48036084



## SCHUKO socket outlet with 2 x USB Berker Q.1/Q.3/Q.7/Q.9

### Technical features

#### Architecture

Fixing mode	flush-mounting
-------------	----------------

#### Connectivity

Type of USB port	AA
- with 2 USB sockets type A	

#### Main electrical features

Nominal voltage	250 V
Rated voltage	250 V
Efficiency at low load (10 %)	76,1 %
Average active efficiency	84,7 %
Frequency	50 Hz
Rated current	16 A

#### Voltage

Input voltage	220...250 V AC
Output voltage	4,75...5,25 V DC

#### Electric current

Input current	max. 500 mA
Output current	2,4 A
Output current when operating both sockets	max. 2400 mA
Output current per socket	max. 2400 mA
Rated current	16 A

#### Fuse

Fuse	short-circuit and overload proof (electronic fuse)
------	--

#### Power

Power consumption (standby)	< 50 mW
Output power	12 W
No-load power consumption	68 mW

#### Cover, door

Cover	Central cover plate
-------	---------------------

#### Materials

Colour	aluminium optics
RAL colour	RAL 9006 - White aluminium
Material	Plastic/metal
Surface appearance	velvety

### Dimensions

Insertion depth	32 mm
-----------------	-------

### Installation, mounting

Installation mode	for flush-mounted and hollow-wall mounting
-------------------	--

### Connection

Conductor cross-section (flexible)	1,5...2,5 mm <sup>2</sup>
------------------------------------	---------------------------

Conductor cross-section (rigid)	1,5...2,5 mm <sup>2</sup>
---------------------------------	---------------------------

- with plug-in terminals

### Equipment

With transparent product label holder	no
---------------------------------------	----

### Safety

IK protection code against mechanical impacts	02
---	----

Protection index IP	IP20
---------------------	------

Enhanced contact protection	according to VDE 0620-1:2021-02
-----------------------------	---------------------------------

### Use conditions

Operating temperature	5...35 °C
-----------------------	-----------

### Identification

Main design line	Berker Q.1/Q.3/Q.7/Q.9
------------------	------------------------

Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9
--------------------------	--