



48031606



SCHUKO socket outlet with 2 x USB with enhanced touch protection, Berker S.1/B.3/B.7, anthracite, matt

Technical features

Architecture

Fixing mode flush-mounting

Connectivity

Type of USB port AA
- with 2 USB sockets type A

Main electrical features

Nominal voltage 250 V
Rated voltage 250 V
Efficiency at low load (10 %) 76,1 %
Average active efficiency 84,7 %
Frequency 50 Hz
Rated current 16 A

Voltage

Input voltage 220...250 V AC
Output voltage 4,75...5,25 V DC

Electric current

Input current max. 500 mA
Output current 2,4 A
Output current when operating both sockets max. 2400 mA
Output current per socket max. 2400 mA
Rated current 16 A

Fuse

Fuse short-circuit and overload proof (electronic fuse)

Power

Power consumption (standby) < 50 mW
Output power 12 W
No-load power consumption 68 mW

Cover, door

Cover Central cover plate

Materials

Colour anthracite
Colour anthracite charcoal grey
RAL colour RAL 7021 - Black grey
Material Plastic/metal
Surface appearance matt

Dimensions

Insertion depth	32 mm
-----------------	-------

Installation, mounting

Installation mode	for flush-mounted and hollow-wall mounting
-------------------	--

Connection

Conductor cross-section (flexible)	1,5...2,5 mm ²
------------------------------------	---------------------------

Conductor cross-section (rigid)	1,5...2,5 mm ²
---------------------------------	---------------------------

- with plug-in terminals

Equipment

With transparent product label holder	no
---------------------------------------	----

Use

Differentiation characteristic 2 - Sales	with enhanced touch protection
--	--------------------------------

Safety

IK protection code against mechanical impacts	02
---	----

Protection index IP	IP20
---------------------	------

Enhanced contact protection	according to VDE 0620-1:2021-02
-----------------------------	---------------------------------

Use conditions

Operating temperature	5...35 °C
-----------------------	-----------

Identification

Main design line	Berker S.1/B.3/B.7
------------------	--------------------

Secondary design line(s)	Berker S.1, Berker B.3, Berker B.7
--------------------------	------------------------------------