



75143865



IP20

Touch sensor 3gang comfort with integral bus coupling unit, KNX - Berker R.1, glass black

Technical features

Architecture

Fixing mode flush-mounting

Functions

With room temperature controller yes

- for switch, push-button, dimmer and shutter functions
- Blocking function for sensor surface e.g. for cleaning the glass surface

Compatibility

- extension unit for light scene push-button

Controls and indicators

With LED indication yes

- operation by gently touching the sensor surfaces on the white LED

Power

Current consumption 12,5 mA

Measurement

- value transmitter for dimming, position, brightness and temperature values 1 and 2 byte

Screen

With display yes

Materials

Colour of design line glass black

Colour black

RAL colour RAL 9005 - Jet black

Material glass

Surface appearance glossy

Type of surface treatment Painted

Dimensions

Depth 23 mm

Height 152 mm

Width 81 mm

LED control

LED with blue operation LED and 6 white status LEDs

Installation, mounting

Installation mode for vertical mounting

Connection

- with integral bus coupling unit
- bus connection via connecting terminal

Scope of delivery

Bus connection included yes

Accessories included

Inscribable, with labelling field no

- for additional products to complement the installation in matching colours/materials, refer to the Design platform R.1/R.3
- for suitable frames in the same "style" for additional applications, see the Design line R.x

Equipment

Number of actuation points 6

With anti-theft/dismantling protection yes

Use

Differentiation characteristic 3 - Sales with integral bus coupling unit

Safety

Protection index IP IP20

Halogen free no

Use conditions

Operating temperature -5...45 °C

- temperature measurement via internal temperature sensor or external communication object
- integrated temperature sensor for operation as controller extension unit
- additional connection for external temperature sensor

Identification

Application, usage KNX - operating systems

Main design line KNX - Berker R.1

Secondary design line(s) KNX, Berker R.1