


2875



## Rotary dimmer 600 W with soft-lock, Light control, others

### Technical features

#### Main electrical features

Nominal voltage	230 V
Frequency	50 Hz

#### Voltage

Operating voltage	230 V AC
- voltage test possible without dismantling	

#### Fuse

Fuse	with spare fuse, short-circuit and overload proof (fine-wire fuse)
------	--------------------------------------------------------------------

#### Power

Loss power at full load	≈ 6 W
-------------------------	-------

#### Materials

Colour	not applicable
Material	Plastic/metal

#### Dimensions

Axis dimension Ø	4 mm
------------------	------

#### Incandescent bulbs control

230 V incandescent lamps and halogen lamps	60...600 W
--------------------------------------------	------------

#### Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

#### Connection

Type of load	Resistive load
- with plug-in terminals	

#### Equipment

- phase cut-on
- with change-over pressure switch

#### Use

Differentiation characteristic 3 - Sales	with soft-lock
------------------------------------------	----------------

#### Safety

Halogen free	yes
--------------	-----

#### Identification

Application, usage	Light control
Main design line	Light control

**Instructions**

---

Information text

Possible to change fuse without removing cover.

---