



286610



Rotary dimmer (R, L) Light control, others

Technical features

Main electrical features

Nominal voltage	240 V
Frequency	50/60 Hz

Voltage

Operating voltage	230 V AC
-------------------	----------

Fuse

Fuse	short-circuit and overload proof (fine-wire fuse)
------	---

Power

Dimmable conventional transformers	20...500 VA
------------------------------------	-------------

Materials

Colour	not applicable
Material	Plastic/metal

Dimensions

Axis dimension Ø	4 mm
------------------	------

Incandescent bulbs control

230 V incandescent lamps and halogen lamps	20...500 W
--	------------

Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

Connection

Type of load	inductive
- with screw terminals	

Equipment

- phase cut-on
- with change-over pressure switch

Identification

Application, usage	Light control
Main design line	Light control

Instructions

Information text	Possible to change fuse without removing cover.
------------------	---

In case of excessive switch-on currents (for conventional transformers), use switch-on current limiters order no. 185.